

Constructed with metal cabinet, the speaker is ideal for use in a voice alarm system. Can be surface- or flush-mounted to the wall. Either concealed in-wall wiring or exposed wiring can be used for speaker cable connection. The speaker structure of direct wall-mounting with screws prevents the speaker from falling easily even if an outward force is applied to. The input impedance can be easily changed by changing the tap position of the transformer. The built-in 16 cm double cone speaker unit delivers high quality sound. The push-in type input connector makes cable connections easy and allows bridge wiring.



Order no: BS-680F

Specifications

Frequency response	150 Hz - 20 kHz
Connection	Push-in connector (briding terminal)
Sensitivity (1#W, 1#m) (combined)	94 dB
Speaker component	16 cm double cone-type
Rated input	6 W, 3 W
Tappings	6 / 3 / 1.5 / 0.8 W (100 V), 3 / 1.5 / 0.8 / 0.4 W (100 V)
Rated impedance	70 V, 100 V
Dimensions (W x H x D)	310 x 190 x 87,2 mm
Dimensions (ø x D)	x 87,2 mm
Finish	Steel plate, off-white (RAL 9010 or equivalent)
Operating temperature	-10°C to +50°C

Appearance

