Freedom Stick X4

- Unique and versatile free-standing LED array that adds pizazz to any event
- · Slip on frosted tubes allow for 2 completely different looks
- Half of the stick can be deactivated to provide a 180° effect saving battery life
- Built-in 3-pin DMX connectors make control compatible with other DMX enabled fixtures
- Control auto and sound programs via DMX, wireless master/slave, or the included RFC remote
- Optional RFC-XL remote allows grouping of several sets of Freedom Sticks without DMX.
- Battery-powered and built-in D-Fi receiver allows the stick to be placed anywhere
- Each LED can be pixel-mapped for ultimate show and programming creativity
- Detachable metal base allows for truss mounting (clamps sold separately)
- User-customizable automated programs create complex looks in seconds



- DMX Channels: 3, 8, 48, 50DMX Connectors: 3-pin XLR
- Light Source: 32 LEDs (tri-color RGB) 0.2 W, (12 mA), 50,000 hours life expectancy
- Strobe Rate: 0 to 30 Hz
- Maximum Run Time (360°): 5 hours
- Maximum Run Time (180°): 10 hours
- · Maximum Run Time (single color): 20 hours
- Recharge Time : 4 hours
- Input Voltage: External power supply: 100 to 240 VAC, 50/60 Hz)
- Power and Current: 11 W, 0.1 A @ 120 V, 60 Hz
- Power and Current: 11 W, 0.1 A @ 230 V, 50 Hz
- Operating Frequency: 2.412 to 2.484 GHz
- Max Unobstructed Distance: 600 ft (183 m)
- Bracket Mounting Hole: M10
- Weight: 3.3 lbs. (1.5 kg)
- Size (fixture): 59 x 6.3 x 6.3 in (1500 x 160 x 160 mm)
- Size (carry bag): 61 x 10.6 x 2.6 in (1550 x 270 x 65 mm)
- Optional Controllers: RFC-XL, FlareCON
- · Approvals: CE, UKCA, RoHS, FCC





