APART D-VOL30

biamp.



70 volt, 30 watts volume controls Decora style



The Apart D-VOL30 is a 70 volt volume control. It can handle up to 30 watts of power and is very durable thanks to the step-by-step attenuation in 11 steps + zero position. The D-VOL30 is designed to handle 24V priority signals. This means that you can always get an announcement out, even to zones where the local volume control is in the 'OFF' position! If your amplifier has a 24V priority output, it will send a 24V signal when you push the talk button on the microphone.

The 24V signal will close a relay on the D-VOL30 volume control, and the signal will pass, even when the volume control is in the 'OFF' position. This can be very useful for emergency or evacuation messages. The D-VOL30 is built on a universal chassis that easily can be integrated with any Decora box offering a flush mount and neat finish.

TECHNICAL SPECIFICATIONS

stereo/mono	mono	applicable low impedance	no
applicable 70V	yes	max. power in watts	30
steps	0 + 11	24 volt priority relais	yes
mounting	screw	connector type	euroblock 6-pole
max. cable in mm ²	2.5	width in mm	70
height in mm	115	depth in mm	47
weight in kg	0.37	Net weight product in kg	0.27

biamp.

MORE PICTURES



