





Designed for exclusive use with the M-8080D, the M-800RC Remote Audio Control Panel has a volume/routing control knob.

.....



Article number:M-800RC-EB

.....

Specifications

Power source	24 V DC (Powered by M-8080D or M-804EX or external)
Indicator	LC-Display Displays device information: ID, Volume, communication status
Inputs	RD In: Transmits and receives AES3 digital audio plus control data Connect to M-8080D, M-804EX or M-800RC, M-800RCT for daisy chain, RJ45 connector
Outputs	RD EXP: Transmits and receives control data Connect to M-800RC or M-800RCT, RJ45 connector
Controls	Volume / Routing
Dimensions (W x H x D)	147 x 86 x 65 mm
Dimensions (ø x D)	x 65 mm
Finish	Polycarbonate, ABS resin, traffic white (RAL 9016 or equivalent), Panel.
Operating humidity	90% RH or less (no condensation)
Operating temperature	0°C to +40°C





Appearance